



Handheld Digital Multimeter

OHDM3751

- Auto range.
- 6000 counts and barograph display.
- Measurement including DCV/ACV (600 V/600 V), DCI/ACI (600 mA/600 mA), Ω (10 m Ω), capacitance (6 mF), continuity test, duty cycle, etc.

Model		OHDM3751
SPECIFICATIONS	RANGE	ACCURACY
DC Voltage	6 V/60 V/600 V	± (0.8%+3)
AC Voltage	6 V/60 V/600 V	± (1.2 %+3)
DC Current	600 mA	± (1.0%+3)
AC Current	600 mA	± (1.5%+3)
Resistance (Ω)	6kΩ/60kΩ/600kΩ/6 MΩ/10 MΩ	± (1.0%+3)
Capacitance (C)	60 nF/600 nF/6 μF/60 μF/600 μF/6 mF	± (4%+5)
Frequency	30~1000 Hz	± (0.5%+2)
Temperature (°C/°F)	-20°C~ 1300°C	± (1.0%+3)
	-4°F~ 2372°F	± (1.0%+3)
Power supply	3x1.5 V AAA batteries	
Weight	Approx. 250g (without batteries)	
Size	169 mmx83mmx53mm	
Safety Rating	EN61010-1, -2-030, EN61010-2-2003 EN1326-1, CAT.III 600 V	
Display	6000 counts	
Auto range		
Barograph display		
True RMS		
Transistor		
NCV		
Live test		
Data hold		
Work light		
Back light		
Auto power off		